



Spectrum Digital CCS/Host OS/Emulator Compatibility Chart

07/15/2011

Emulator Type	Part Number	Host Interface	CC 4.10 for C3x/C4x	CC 4.10	CCS 2.2x	CCS 3.1	CCS 3.2	CCS 3.3	CCS 4.x	CCS 5.x	SDFlash Programming Utility	XMLGUI Support
XDS510PP MPD ¹	701041	PP	1,2,3									
SPI530 MPD ¹	701121	PP	1,2,3									
XDS510PP PLUS ¹	701014	PP	1,2,3	1,2,3	1,2,3,4	3,4	3,4	3,4,5	4,5,6	4,5,6	☺	☺
SPI510 ¹	701250	ISA	1,2,3	1,2,3	1,2,3,4	3,4	3,4	3,4,5	4	4	☺	
SPI515 ¹	701515	PP	1,2,3	1,2,3	1,2,3,4	3,4	3,4	3,4,5	4	4	☺	
SPI525 ¹	701700	PCI	1,2,3	1,2,3	1,2,3,4	3,4	3,4	3,4,5	4	4	☺	
C2000 XDS510LC	701902	USB				3,4	3,4	3,4,5	4,5,6	4,5,6,7	☺	☺
XDS510 USB	701900	USB	3,4			3,4	3,4	3,4,5	4,5,6	4,5,6,7	☺	☺
XDS510USB PLUS	701905/7	USB				3,4	3,4	3,4,5	4,5,6	4,5,6,7	☺	☺
XDS510USB Galvanic	701910	USB				3,4	3,4	3,4,5	4,5,6	4,5,6,7	☺	☺
XDS560R ²	702560/2	USB				3,4	3,4	3,4,5	4,5,6			
XDS560v2 ³	702592	USB/ Enet							4,5,6	4,5,6,7		
XDS560v2 Traveler ³	702598	USB							4,5,6	4,5,6,7		
XDS100v1	702300	USB						3,4,5	4,5,6			
XDS100v2	702302	USB							4,5,6	4,5,6,7		
XDS100v3	702304	USB							4,5,6	4,5,6,7		

Operating System	Key
Win 98 SE	1
Win NT	2
Win 2000	3
Win XP	4
Win Vista	5
Win 7	6
Linux	7

- ¹ – Non-USB emulators do not support 64-bit OSes.
² – XDS560R does not support CCS 4.1.3 or later.
³ – XDS560v2 supports CCS 4.2 and later.



Kane Computing Ltd
 Suite 1, Ascot Court,
 71-73 Middlewich Road,
 Northwich, Cheshire, CW9 7BP.
 Tel: +44(0)1606 351006
 Fax: +44(0)1606 351007
 Email: sales@kanecomputing.com
 Web: www.kanecomputing.co.uk